

Battery Cable Length		
Description	Length	Termination
1987-1990 Cherokee & Comanche w/2.5L		
B+ to Starter Motor	38"	3/8" x 3/8"
B+ to Starter Motor Relay/Distribution	8"	3/8" x 3/8"
B- to Engine Block	26"	3/8" x 3/8"
Engine Block to Firewall	14"	1/2" x 1/2"
B- to Alternator Case (Optional)	26"	3/8" x 3/8"
B- to Fenderwell (Optional)	10"	1/4" x 3/8"
Alternator Output to Starter Motor Relay/Distribution	26"	1/4" x 3/8"
1987-1990 Cherokee & Comanche w/4.0L		
B+ to Starter Motor	38"	3/8" x 3/8"
B+ to Starter Motor Relay/Distribution	10"	3/8" x 3/8"
B- to Engine Block	36"	3/8" x 3/8"
Engine Block to Firewall	10"	3/8" x 1/2"
Alternator Case to B- (<i>Optional</i>)	30"	3/8" x 3/8"
B- to Fenderwell (<i>Optional</i>)	10"	1/4" x 3/8"
Alternator to PDC	24"	3/8" x 3/8"
1991-1995XJ w/4.0L, 1991-1992MJ w/4.0L		
B+ to Starter Motor	32"	3/8" x 3/8"
B+ to PDC	16"	3/8" x FAQ #9
B- to Fenderwell	8"	3/8" x 3/8"
Engine Block to Firewall	10"	3/8" x 1/2"
B- to Engine Block	32"	3/8" x 3/8"
Alternator to PDC	30"	1/4" x FAQ #9
1996 Jeep Cherokee w/4.0L		
B+ to Starter Motor	32"	3/8" x 3/8"
B+ to PDC	16"	3/8" x FAQ #9
B- to Fenderwell	8"	3/8" x 3/8"
Engine Block to Firewall	10"	3/8" x 1/2"
B- to Engine Block	28"	3/8" x 3/8"
Alternator to PDC	28"	1/4" x FAQ #9
1997-2001 Jeep Cherokee w/4.0L		
B+ to Starter Motor	38"	3/8" x 3/8"
B+ to PDC	18"	3/8" x FAQ #9
B- to Fenderwell	8"	3/8" x 3/8"
Engine Block to Firewall	10"	3/8" x 1/2"
B- to Engine Block	28"	3/8" x 3/8"
Alternator to PDC	36"	1/4" x FAQ #9
1993-1994 Jeep Grand Cherokee w/4.0L		
B+ to Starter Motor	38"	3/8" x 3/8"
B+ to PDC	10"	3/8" x FAQ #9
B- to Fenderwell	10"	3/8" x 3/8"
B- to Engine Block	32"	3/8" x 3/8"
Alternator to PDC	18"	1/4" x FAQ #9
All credit to Kelly's WIP/5-90		
Maintained by /u/toaster_knight		